

OPERATING PRINCIPLES

The address of each call point is set at the commissioning stage by means of a seven-segment DIL switch.

A single bi-coloured alarm LED is provided on the call point. This LED is controlled independently of the call point, by the control panel. The LED is illuminated red when the call point has been activated. The LED is illuminated amber/yellow LED to indicate a short circuit.

This Manual Call Point helps reduce installation time as all the initial installation cabling is wired to a terminal block which fits neatly in the back of the call point.

Once activated, the Discovery Waterproof Manual Call Point can be reset by inserting the test key into the bottom of the unit until the key clicks into position. Remove the test key and push the front cover up until it clicks home.

The isolated version of the Discovery Waterproof Manual Call Point incorporates a short circuit isolator which will ensure its operation in the event of a short circuit fault on the loop. Full details of the isolator can be found in the PIN Sheet PP2090, available on request.

TECHNICAL DATA

Supply voltage	17–28V DC
Communications protocol	5–9V peak to peak
Maximum current consumption, at 24V	
Quiescent	100µA
power-up surge, 1 second typical	1mA
Alarm LED on	4mA
Operating temperature	–30°C to +70°C
Humidity (no condensation)	0–95%RH
IP rating	67
Complies with EMC Directive 2004/108/EC Complies with EN54–11:2001 and EN54–17:2005 (isolated version)	

EMC DIRECTIVE 2004/108/EC

The Discovery Waterproof Manual Call Point complies with the essential requirements of the EMC Directive 2004/108/EC, provided that it is used as described in this PIN sheet.

A copy of the Declaration of Conformity is available from Apollo on request.

Conformity of the Discovery Waterproof Manual Call Point with the EMC Directive does not confer compliance with the directive on any apparatus or systems connected to it

DIMENSIONAL DRAWING

