

XP95A

Mini Priority Switch Monitor Module



Product overview

Product	Mini Priority Switch Monitor Module
Part No.	55000-830
Digital communication	XP95 compatible only

Compliance



Product information

The XP95A Mini Priority Switch Monitor Module is designed to fit into equipment with limited space and monitor the state of one or more single-pole, volt-free contacts and to report the status to Apollo compatible analog control equipment. It can also place a signal on the loop to provide early warning if a device such as a pull station is operated.

- Three input states - 'normal', 'alarm' and 'trouble'
- Visible LED with remote LED connection option
- Loop-powered
- Designed to fit into equipment with limited space
- Easy to install
- Monitors equipment where a fast response is required
- Interrupt facility

Technical data

All data is supplied subject to change without notice. Specifications are typical at 24 V, 73°F and 50% RH unless otherwise stated.

Single line circuit (SLC)	Supervised power limited
Working Voltage	17V - 28 V dc
Modulation voltage	5 - 9 V peak to peak
Supervisory current	1 mA
Surge current	2.5 mA
Maximum alarm current	5.0 mA (LED on)
Analog level (normal)	16
Analog level (alarm)	64
Analog level (trouble)	4
Initiating device circuit (IDC)	
Wiring styles	Supervised power limited Class A and Class B
Voltage	10 V dc
Current	1.7 mA max
Line impedance	100 Ω max
End-of-line resistors*	47 kΩ
General	
Digital communication	XP95
Application	Indoor/dry
Temperature range	32°F to 120°F (0°C to 49°C)
Humidity (no condensation)	0% to 95% RH
Standards and approvals	UL, ULC, CSFM
Dimensions	3 in. (76 mm) x 2 in. (50 mm) x 0.5 in. (12 mm)
Material	White flame-retardant polycarbonate

Note: A UL listed end-of-line resistor is available from Apollo, Part No. 44251-146.

Mechanical description

The Mini Priority Switch Monitor Module is supplied as a PCB in a two-part polycarbonate molding with connections being made by six 150 mm flying leads. The address switch is accessible through an aperture in the molding. When the address has been set the aperture must be sealed with the label provided that should show the setting of the address switch.

The device is fitted with an LED which illuminates red in alarm. A remote LED connection is also provided which is switched with the integral LED.

Protocol compatibility

The XP95A Mini Priority Switch Monitor Module operates only with control equipment using the Apollo Series 90, XP95, Discovery or CoreProtocol protocols.

This page has intentionally been left blank